Mrd 04/04/02 CLMPTO

1-12 (cancelled).

13. (New) A method for estimating a memory-enabled transmission channel, comprising the steps of:

determining a first estimation $\hat{\underline{h}}$ of a pulse response of the memory-enabled transmission channel;

performing an estimation of an additive interference of the memory-enabled transmission channel; and

performing a correction of the first estimation while taking into consideration the estimation of the additive interference.

14. (New) The method according to claim 13, wherein:

the step of determining the first estimation is performed by a matched filter.

15. (New) The method according to claim 14, wherein:

the matched filter is given by

$$\hat{\underline{h}} = \frac{1}{\gamma} \cdot G^{*T} \cdot \underline{e}_{M},$$

where

$$G = \begin{pmatrix} r_W & r_{W-1} & \cdots & r_1 \\ r_{W+1} & r_W & & r_2 \\ \vdots & \vdots & & \vdots \\ r_{W+N-1} & r_{W+N-2} & \cdots & r_N \end{pmatrix}$$

and

BEST AVAILABLE COPY

13. (New) A method for estimating a memory-enabled transmission channel, comprising the steps of:

determining a first estimation $\hat{\underline{h}}$ of a pulse response of the memory-enabled transmission channel;

performing an estimation of an additive interference of the memory-enabled transmission channel; and

performing a correction of the first estimation while taking into consideration the estimation of the additive interference.

14. (New) The method according to claim 13, wherein:

the step of determining the first estimation is performed by a matched filter.

15. (New) The method according to claim 14, wherein:

the matched filter is given by

$$\underline{\hat{h}} = \frac{1}{\gamma} \cdot G^{*T} \cdot \underline{e}_{ml},$$

where

$$G = \begin{pmatrix} r_W & r_{W-1} & \cdots & r_1 \\ r_{W+1} & r_W & & r_2 \\ \cdot & \cdot & & \cdot \\ r_{W+N-1} & r_{W+N-2} & \cdots & r_N \end{pmatrix}$$

and

BEST AVAILABLE COPY

19. (New) The method according to claim 13, wherein:

the correction of the first estimation $\hat{h}_k$ of the k^{th} component, $k \in \{1,\ldots,W\}$, of estimation vector $\underline{\hat{h}}$ of the pulse response $\underline{h}$ is given by

$$\hat{h}_k = \begin{cases} 0, \text{ if } \hat{h}_k^2 < \sigma^2/\gamma \\ \text{otherwise } \hat{h}_k \end{cases}$$

20. (New) The method according to claim 13, wherein:

the correction of the first estimation $\hat{h}_k$ of the k^{th} component, $k \in \{1,\ldots,W\}$, of estimation vector $\underline{\hat{h}}$ of the pulse response $\underline{h}$ is given by

$$\hat{h}_k = \sqrt{\theta\left(\hat{h}_k^2 - \sigma^2/\gamma\right)} \cdot \hat{h}_k / \left|\hat{h}_k\right|, \text{ if } \hat{h}_k \neq 0, \text{ and}$$

otherwise

$$\hat{h}_k = 0$$

21. (New) The method according to claim 13, wherein:
the correction of the first estimation is given by a POCS algorithm.

22. (New) The method according to claim 13, wherein:
the correction of the first estimation is given by a MMSE algorithm.

BEST AVAILABLE COPY

23. (New) The method according to claim 22, wherein:

the MMSE algorithm is given by

$$\hat{\underline{h}} = \left(G^{*T} \cdot G + \sigma^2 \cdot \mathrm{I}\right)^{-1} \cdot G^{*T} \cdot \underline{e}_{sr}$$

I being the unit matrix.

24. (New) A device for estimating a memory-enabled transmission channel, comprising:

a channel estimator;

an estimator of an additive interference, the channel estimator and the estimator of the additive interference act on a received signal; and

a channel estimation correcting element for correcting a signal of the channel estimator while taking into consideration an output signal of the estimator of the additive interference.

260001

BEST AVAILABLE COPY

This Page is Inserted by IFW Indexing and Scanning Operations and is not part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☒ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☐ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.
As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.